

Determination of the relaxation time distribution from the dielectric losses

S.A. Ktitorov

*A.F. Ioffe Physico-Technical Institute of the Russian Academy of Sciences,
Polytechnicheskaja str. 26, St. Petersburg 194021, Russia*

A problem of determining of the relaxation time distribution in irregular relaxing systems is considered from the point of view of the Kotelnikov-Shannon theorem of the telecommunication theory.

The dielectric relaxation in irregular systems like polymers, impure ferroelectrics etc, and magnetic relaxation in impure magnetics including spin glasses [1] are usually described with a help of a continuous relaxation time distribution function (RTDF). It is desirable to have, along with theoretical models for such distributions, some regular technique for determining of them using the measured experimentally dielectric $\epsilon(\omega)$ or magnetic $\mu(\omega)$ spectrum. We will discuss for definiteness the former case. The exact formula relating the dielectric losses and RTDF was derived in [2] many years ago. However, this formula can not be used directly in practice (see the discussion below). Numerical analysis of the proper integral equation was done recently [3], [4]. Our aim here is to develop an approach giving a practical procedure for determining of RTDF.

We introduce RTDF $g(\ln(\tau/\tau_0))$ with a help of the relation [5]:

$$\chi(\mu) = \int_{-\infty}^{\infty} \chi_D(\omega\tau) g(\ln(\tau/\tau_0)) d\ln(\tau/\tau_0) \quad (1)$$

with

$$\chi_D(\omega\tau) = \frac{\epsilon_D(\omega\tau) - \epsilon_\infty}{\epsilon_0 - \epsilon_\infty} = \frac{1}{1 - i\omega\tau}, \quad (2)$$

where $\epsilon_D(\omega\tau)$ is the Debye single-relaxator dielectric permittivity, ϵ_0 and ϵ_∞ are respectively zero- and high-frequency limits of the permittivity, τ_0 is an arbitrary time scale. Basing on rather intuitive grounds, the distribution function is often estimated assuming $g(\ln(\tau/\tau_0)) = \text{Im } \chi(\ln(\omega\tau_0))$. Our aim here is to give a regular procedure for calculation of the distribution function $g(\ln(\tau/\tau_0))$ basing on a measured dielectric spectrum $\epsilon(\omega)$.

Let us introduce the logarithmic variables:

$$\begin{aligned} z &= \ln(\tau/\tau_0); \omega\tau_0 = \Omega; \tau/\tau_0 = \exp(z), \Omega = \exp(-\mu), \\ \omega\tau &= \Omega \exp(z) = \exp(z - \mu), y = -\ln(\omega\tau_0), \end{aligned} \quad (3)$$

Then equation (1) can be rewritten in the form

$$\chi(y) = + \int_{-\infty}^{\infty} dx \frac{g(x)}{1 - i \exp(x - y)}. \quad (4)$$

Now we discuss some possible approaches to the problem. The integral equation (4) can be solved exactly. This equation belongs to the class of equations that can be solved using the Fourier transform. Taking the imaginary part we have

$$\chi''(\omega) = \int_{-\infty}^{\infty} d\ln(\tau/\tau_0) \frac{g(\ln(\tau/\tau_0)) \omega\tau}{1 + (\omega\tau)^2}. \quad (5)$$

Introducing the logarithmic variables we can write

$$\chi''(\mu) = \int_{-\infty}^{\infty} dz \frac{g(z) \Omega \exp(z)}{1 + \Omega^2 \exp(2z)} = \int_{-\infty}^{\infty} dz \frac{g(z) \exp(z - \mu)}{1 + \exp(2(z - \mu))} = \frac{1}{2} \int_{-\infty}^{\infty} dz \frac{g(z)}{\cosh(z - \mu)}. \quad (6)$$

Let us write (6) in the standard form

$$\chi''(\mu) = \int_{-\infty}^{\infty} dz K(\mu - z)g(z). \quad (7)$$

This integral equation can be solved using the Fourier transform:

$$\chi_y'' = \int_{-\infty}^{\infty} dz \exp(iyz) \chi''(z), \quad (8)$$

$$g_y = \int_{-\infty}^{\infty} dz \exp(iyz) g(z), \quad (9)$$

$$K(z - \mu) = 1/[2 \cosh(z - \mu)]. \quad (10)$$

Performing the Fourier transform we obtain an algebraic equation relating the Fourier transformants:

$$\chi_y'' = K_y g_y. \quad (11)$$

Using the known integral [7]

$$\int_0^{\infty} dx \frac{\cos xy}{\cosh \alpha x} = \frac{\pi}{2\alpha \cosh(\frac{\pi y}{2\alpha})}, \quad (12)$$

we can write

$$K_y = \pi/[2 \cosh(\pi y/2)]. \quad (13)$$

Thus the Fourier transform of the solution reads

$$g_y = 2\pi^{-1} \chi_y'' \cosh(\pi y/2).$$

Taking the inverse Fourier transformation

$$g(z) = \int_{-\infty}^{\infty} \frac{dy}{2\pi} \exp(-iyz) g_y, \quad (14)$$

we can, in principle, calculate RTDF basing on the measured dielectric losses function $\chi''(\mu)$. These integrals must be computed numerically if the susceptibility is presented as a point numerical function. The trouble with this way is the extremely poor convergence of the integral with respect to μ . However, there is another possible way: if we can carry out an analytic continuation of the dielectric losses function we can integrate generically. We assume the integrals to be uniformly convergent within the domain of integration so that one can change the order of integration (an exact analysis must be carried out on the base of the theory of distributions [?]):

$$\begin{aligned} g(z) &= \frac{1}{2\pi^2} \int_{-\infty}^{\infty} dy \int_{-\infty}^{\infty} d\mu \exp[(\mu - z)yi] \chi''(\mu) [\exp(\pi y/2) + \exp(-\pi y/2)] = \\ &= \frac{1}{\pi} \int_{-\infty}^{\infty} d\mu \chi''(\mu) [\delta(z - \mu + i\pi/2) + \delta(z - \mu - i\pi/2)] = \end{aligned}$$

$$= \frac{1}{\pi} [\chi''(z + i\pi/2) + \chi''(z - i\pi/2)] \quad (15)$$

This solution was derived by Kirkwood [2] in a different way.

Now we discuss possible ways for practical use of this formula. Assuming differentiability of $\chi''(z)$ up to at least the second derivative and its slowness and expanding it in powers of $i\pi/2$, we can give the approximate form of the solution:

$$g(z) \approx \frac{2}{\pi} \left[\chi''(z) - \frac{\pi^2}{8} \frac{d^2 \chi''(z)}{dz^2} + \dots \right]. \quad (16)$$

This approximate formula is asymptotically exact for very slowly-varying dielectric functions. Formula 15 can be basically used in a general case, but ambiguity of the analytic continuation makes it problematic. There are two main reason for it. Firstly, results of the analytic continuation essentially depend on analytic properties of the function, but they cannot be established exactly basing on a function determined on the finite segment of the real axis. Secondly, measuring of the dielectric losses function yields really a discrete set of points that presents an additional ambiguity factor. This means that analytic properties must be determined independently. A similar problem exists in the communication theory. Discretization of a signal and impossibility to transfer a signal with unlimited spectrum through the channel make it necessary to apply the approach developed in the communication theory by Kotelnikov and Shannon [8] (basically similar approach was really known earlier in the mathematical theory of approximation). Following to the spirit of this approach, we assume that $\chi''(z)$ is an entire function of finite degree [8]:

$$\lim_{r \rightarrow \infty} \frac{\ln \max_{|z|=r} |\chi''(z)|}{r^2} = \alpha < +\infty \quad (17)$$

But according to the Paley-Wiener theorem [6], such a function has a bounded spectrum. What does it mean from the physical point of view in our case? The spectrum of $\chi''(z)$ characterizes the time evolution of the polarization; therefore, boundness of the spectrum means that a reaction of the polarization on the field pulse decays for some finite time. Surely, this decay time is theoretically infinite in glasses, but it is essentially restricted by noise and other factors in a real experiment. That is why we have right to assume $\chi''(z)$ to be an entire function of finite degree.

Let $\chi''(z)$ be a function with the spectrum g_y given by 9 lying in the band $-\beta < y < \beta$. Then the following interpolating formula holds for $\chi''(z)$ at $\alpha > \beta$:

$$\chi''(z) = \sum_{k=-\infty}^{\infty} \chi''(k\frac{\pi}{\alpha}) \frac{\sin \alpha (z - k\frac{\pi}{\alpha})}{\alpha (z - k\frac{\pi}{\alpha})}. \quad (18)$$

This series converges uniformly to the entire analytic function and admits an analytic continuation. Substituting (15) into (18) we come to the final formula:

$$g(z) = \frac{1}{\pi} \sum_{k=-\infty}^{\infty} \chi''(k\frac{\pi}{\alpha}) \left[\frac{\sin \alpha (z + i\frac{\pi}{2} - k\frac{\pi}{\alpha})}{\alpha (z - k\frac{\pi}{\alpha})} + \frac{\sin \alpha (z - i\frac{\pi}{2} - k\frac{\pi}{\alpha})}{\alpha (z - k\frac{\pi}{\alpha})} \right] =$$

$$\frac{\cosh \frac{\alpha\pi}{2}}{\pi} \sum_{k=-\infty}^{\infty} \chi''(k\frac{\pi}{\alpha}) \frac{\sin \alpha (z - k\frac{\pi}{\alpha})}{\alpha (z - k\frac{\pi}{\alpha})} \quad (19)$$

Thus, we have shown that for the case of the finite-time response functions, the "naive" solution $g(z) \propto \chi''(z)$ is exact within the class of the entire analytic functions. Notwithstanding the fact that a real measurement gives only finite-time response because of the noise effect, it would be interesting to generalize this result to the case functions, which have an infinite spectrum with power-law decreasing. We hope to return to this problem in the future.

- [2] R.M. Fuoss and J.G. Kirkwood, J. Am. Chem. Soc., **63**, 385 (1941).
- [3] H. Schäfer, E. Sternin, R. Stannarius, M. Arndt, and F. Kremer, Phys. Rev. Lett. **76**, 2177 (1996).
- [4] R. Pelster, T. Kruse, H.G. Krauthäuser, G. Nimtz, and P. Pissis, Phys. Rev. B **57**, 8763 (1998).
- [5] C.J.F. Böttcher, *Theory of Electric Polarisation*, Elsevier Publishing Company, Amsterdam, Houston, London, New York, 1952.
- [6] E.C. Titchmarsh, *Introduction to the Theory of Fourier integrals*, New York, 1937.
- [7] I.S. Gradstein and Ryzhik, *Tables of Integrals, Sums, Series and Products*, Physics and Mathematics Publishing, Moscow, 1963.
- [8] Ya.I. Hurgin and V.P. Yakovlev, *Methods of Entire Functions in Radiophysics, Communication Theory and Optics*, Physics and Mathematics Publishing, Moscow, 1962.
- [9] L. Schwartz, *Méthodes Mathématiques pour les Sciences Physiques*, Hermann, 115, Boulevard Saint-Germain, Paris VI, 1961.